



Production Technology Support

CAMERA PRODUCTION GUIDE | ARRI ALEXA Mini LF

Settings and best-practices for capture with the ARRI ALEXA Mini LF (Software Update Package SUP 6.0.15 and later) on Netflix 4K Originals.

If you have any questions or comments please contact: prodtech.support@netflix.com

Current ALEXA Mini LF Ops Manual: [HERE](#) (scroll down to “Downloads”).

ALEXA Mini LF Frequently Asked Questions (FAQ): [HERE](#).

CAPTURE SETTINGS | 4K RAW (ARRIRAW)

SETTING	MENU NAVIGATION	SELECTION
RECORDING CODEC	MENU → RECORDING → RECORDING CODEC →	ARRIRAW
RECORDING RESOLUTION	MENU → RECORDING → RECORDING RESOLUTION →	LF 16:9 UHD LF Open Gate 4.5K LF 2.39:1 4.5K

Preferred setting shown in **YELLOW & BOLD** and alternatives in normal text.

Note 1: ARRIRAW contains the uncompressed and unencrypted raw sensor data without any debayering, sensitivity setting (Exposure Index - EI), white balance (WB), image processing (Log C, Rec 709 or ARRI Look File ALF-2), noise reduction, image transforms (mirror horizontally, rotate 180°), up/downscaling or anamorphic de-squeezing applied to the recorded image. For more information on ARRIRAW go [HERE](#).

Note 2: The settings chosen for the monitor path (see settings listed in Note 1), including the full ARRI Look File ALF-2, are stored in metadata within the ARRIRAW file. Having the look file attached to the essence is handy for automated dailies creation, editing with looks and as a reference for final grading. During the debayering process



Production Technology Support

(creating a full color image from ARRIRAW) it is possible to have all these settings automatically applied to the image, or to choose alternate settings manually.

Note 3: ARRIRAW images can be viewed and debayered with the free-of-charge ARRI Reference Tool (ART). The ARRI Reference Tool can be downloaded [HERE](#).

Note 4: The SMPTE Registered Disclosure Documents RDD 30 and 31, which contain the ARRIRAW image specifications, will be updated to include the ALEXA Mini LF's MXF/ARRIRAW in addition to the traditional ARRIRAW (.ari).



Production Technology Support

CAMERA PRODUCTION GUIDE | ARRI ALEXA Mini LF

CAPTURE SETTINGS | 4K COMPRESSED

SETTING	MENU	SELECTION
RECORDING CODEC	MENU → RECORDING → RECORDING CODEC →	Apple ProRes 4444 XQ Apple ProRes 4444 Apple ProRes 422 HQ
RECORDING RESOLUTION	MENU → RECORDING → RECORDING RESOLUTION →	LF 16:9 UHD LF Open Gate 4.5K LF 2.39:1 4.5K

Preferred setting shown in **YELLOW & BOLD** and alternatives in normal text.

Note 1: Apple ProRes is a compressed full color image format that has debayering, sensitivity (Exposure Index - EI), white balance (WB), image processing (Log C), noise reduction (if turned on), image rotation (if chosen) and up/downscaling (if chosen) permanently applied to the image. For more information on Apple ProRes go [HERE](#).

Note 2: The ALEXA Mini LF can only record Apple ProRes with Log C image processing. It is not possible to record an image with a look baked-in. However, the settings chosen for the monitor path, including the full ARRI Look File ALF-2, are stored in metadata within the recorded Apple ProRes file. Having the look file attached to the essence is handy for automated dailies creation, editing with looks and as a reference for final grading.

Note 3: Noise Reduction is off by default and can be turned on in MENU > SYSTEM > SENSOR > NOISE REDUCTION. Netflix prefers to not use noise reduction in-camera, since more sophisticated algorithms can be used in post.



CAMERA PRODUCTION GUIDE | ARRI ALEXA Mini LF

HIGH SPEED | 4K RAW (ARRIRAW)

INTERNAL RAW RECORDER	MAX FPS	MAX RESOLUTION
Internal	60 fps	Recording Resolution LF 2.39:1 4.5K (4448 x 1856)
	60 fps	Recording Resolution LF 16:9 UHD (3840 x 2160)
	40 fps	Recording Resolution LF Open Gate 4.5K (4448 x 3096)

HIGH SPEED | 4K COMPRESSED (Apple ProRes)

INTERNAL RECORDER	MAX FPS	MAX RESOLUTION
All Apple ProRes flavors	60 fps	Recording Resolution LF 2.39:1 4.5K (4448 x 1856)
	60 fps	Recording Resolution LF 16:9 UHD (3840 x 2160)
	40 fps	Recording Resolution LF Open Gate 4.5K (4448 x 3096)

Preferred setting shown in **YELLOW & BOLD** and alternatives in normal text.

Note: If you need higher speeds, please use the ALEXA LF, which can run up to 150 fps in the LF 2.39:1 ARRIRAW recording format.



Production Technology Support

CAMERA PRODUCTION GUIDE | ARRI ALEXA Mini LF

OPTIMIZING PERFORMANCE | MAINTENANCE PROCEDURES

Online Tools and Applications

A number of useful ARRI tools, including the Frame Line & Lens Illumination Tool, Camera Simulators, Formats & Data Rate Calculator, ARRIRAW Converter, ARRI Color Tool and ARRI Meta Extract are available in the [TOOLS & APPS](#) section of the ARRI website.

Lens Coverage - General

While the sensor areas of the LF Open Gate and LF 2.39:1 recording resolutions require a full frame lens (or a Super 35 lens with an appropriate expander), the LF 16:9 recording resolution can be covered by the illumination area of many Super 35 PL mount lenses. These lenses can be attached to the ALEXA LF or ALEXA Mini LF by using the PL-to-LPL Adapter. To check which lens covers which sensor mode, see the next note and/or look in the online [ARRI Frame Line & Lens Illumination Tool](#) (click [HERE](#)). ARRI is continuously expanding the tool's library of lenses. Please note that this tool shows how much light is available in the corners of the image, but makes no claim as to the image quality.

Lens Coverage - ARRI Super 35 Lenses for LF 16:9 Recording Resolution

The following ARRI Super 35 lenses have an illumination area that covers the LF 16:9 recording resolution:

- Ultra Primes \geq 20 mm
- Master Primes \geq 35 mm
- Master Macro 100
- Ultra Wide Zoom 9.5 – 18 \geq 10 mm
- Alura LWZ 15.5 – 45 with Alura Extender 1.4x
- Alura LWZ 30 – 80 mm
- Alura Studio zoom 18 – 80 from 40 mm on without extender
- Alura Studio zoom 18 – 80 with Alura Extender 1.4x



Production Technology Support

- Alura Studio zoom 45 – 250 from 100 mm on
- Alura Studio zoom 45 – 250 with Alura Extender 1.4x

Note: Netflix recommends that lenses not specifically designed for large format should be thoroughly tested for adequate sensor coverage, and for the satisfaction of the production's creative intent.

Lens Coverage - ALEXA LF, Mini LF and Anamorphic Lenses

While full frame anamorphic lenses are slowly entering the market, shooting with existing 35 format anamorphic lenses is also possible by using LF Open Gate and cropping the desired area from the image in post-production. A Netflix approved ARRI white paper with details can be downloaded from the ALEXA LF webpage [HERE](#) (scroll down to the DOWNLOADS section and click on the document "ALEXA LF & Anamorphic Lenses White Paper").

Amongst other topics, the white paper covers two methods for shooting with anamorphic lenses compatible with Netflix' 4K mandate:

- When shooting with 35 format 2x anamorphic lenses for a 2:1 aspect ratio result, Netflix accepts the use of a 2880 x 2880 area on the ALEXA LF and ALEXA Mini LF sensor. All Master Anamorphic lenses cover this area. To use this method, create a 2880 x 2880 custom frameline in the **ARRI Frame Line & Lens Illumination Tool** (click [HERE](#)), shoot LF Open Gate and crop 2880 x 2880 in post.
- When shooting with 35 format 2x anamorphic lenses for a 2.39:1 aspect ratio result, Netflix accepts the use of a 3148 x 2636 area on the ALEXA LF and ALEXA Mini LF sensor (if you have gotten Netflix approval for delivering 2.39:1). Master Anamorphic lenses from 40 mm on cover this area, and the ARRI Anamorphic Ultra Wide Zoom AUWZ 19-36 covers this area from 21 mm on for wide angle shots. To use this method, create a 3148 x 2636 custom frameline in the **ARRI Frame Line & Lens Illumination Tool** (click [HERE](#)), shoot LF Open Gate and crop 3148 x 2636 in post.



Production Technology Support

Using HDE for smaller ARRIRAW Files

While ARRIRAW is recorded uncompressed in-camera, the ARRIRAW file size can be reduced during the download process by about 40% through Codex High Density Encoding (HDE). HDE is part of the free-of-charge and license-free Codex Device Manager 5.0 or later software that must run on the Mac receiving the files. HDE is a lossless encoding technique, so the original ARRIRAW files are bit-identical to an ARRIRAW files after HDE decoding. Many third parties already support HDE natively in their software. To learn more about HDE, have a look at ARRI's ARRIRAW FAQ [HERE](#) and choose "HDE / High Density Encoding" from the "Select your option" pull-down menu. To download the latest Codex Device Manager, go [HERE](#).

MXF/ProRes

Please note that the ALEXA Mini LF is the first ARRI camera to use MXF/Apple ProRes instead of QuickTime/Apple ProRes. The ProRes encoding and image quality is the same, but ARRI is changing the wrapper to MXF for ALEXA Mini LF and future cameras. Run a test with your post facility of choice to make sure that their tools support MXF/Apple ProRes. A listing of compatible tools (ALEXA Mini LF Supporting Tools and Software Overview.pdf) can be found in the DOWNLOADS section of the [ALEXA Mini LF Web page](#).

Black Bars in MXF/Apple ProRes Files

The MXF/Apple ProRes files recorded in "LF Open Gate 4.5K" and "LF 2.39:1 4.5K" recording resolutions will show a vertical black bar left and right when played back. This is because the container format required by ProRes is slightly wider than the image content and the MXF playback software cannot automatically crop this area yet. You will have to crop it manually. We expect the MXF playback software to catch up by the time we release the next ALEXA Mini LF Software Update Package (Mini LF SUP 7.0). In case of the "LF 16:9 UHD" recording resolution, the container has the same size as the image content.

Recording Resolutions

The recording resolution **LF Open Gate 4.5K** provides the maximum sensor area (36.70 mm x 25.54 mm) and



Production Technology Support

maximum resolution (4448 x 3096 photosites) for maximum flexibility in post. This recording resolution is covered by full frame lenses, the ARRI Master Macro 100 and by some Super 35 lenses with expanders. The maximum frame rate is 40 fps. Since the entire sensor is recorded, surround view is not available and this recording resolution has the highest data rate.

The recording resolution **LF 16:9 UHD** covers the smallest area (31.68 mm x 17.82 mm) that still meets Netflix 4K deliverable standards with its 3840 x 2160 photo sites. Full frame lenses cover this, of course, but the use of Super 35 lenses is also possible, maximizing lens options. LF 16:9 UHD has surround view available. The maximum frame rate is 60 fps.

The recording resolution **LF 2.39:1 4.5K** provides a cinematic widescreen image (36.70 mm x 15.31 mm - 4448 x 1856) when using large format spherical lenses. This recording resolution has the lowest data rate. In order to maximize frame rate, no surround view is available.

Calculating Crop Factors

The crop factor is the factor by which a focal length has to be multiplied to get the same angle of view on a larger sensor. Crop factors are easy to calculate if both sensors have the same photosite size, as is the case with all ARRI digital cameras. It is important to use the photosite count for the actual framelines one will use.

Crop factor = larger horizontal photosite count divided by smaller horizontal photosite count

Example 1: LF Open Gate (4448 photosites wide) and S35 ALEXA SXT 16:9 2.8K (2880 photosites wide)
 $4448 / 2880 = 1.54$

To get the same angle of view that a 50 mm lens produces on a S35 ALEXA SXT in 16:9 2.8K recording format, you need a 77 mm lens on the ALEXA Mini LF in LF Open Gate recording format ($50 * 1.54 = 77$).

Example 2: LF Open Gate (4448 photosites wide) and S35 ALEXA Mini Open Gate (3424 photosites wide)
 $4448 / 3424 = 1.3$

To get the same angle of view that a 50 mm lens produces on a S35 ALEXA Mini in Open Gate recording format, you



Production Technology Support

need a 65 mm lens on the ALEXA Mini LF in Open Gate recording format ($50 * 1.3 = 65$).

Monitoring HDR

In order to properly monitor ALEXA image on a High Dynamic Range (HDR) monitor, you can either load one of the HDR ARRI Look Files (ALF-2) provided in the camera or create your own. By default, there are a number of look files stored in the camera for either Dolby PQ (Perceptual Quantizer) or HLG (Hybrid Log Gamma) tone mapping. This works with the HD and UHD MON OUT settings. For more information on High Dynamic Range (HDR) go [HERE](#).

Black Balance

It is neither necessary nor possible to manually black balance an ARRI digital camera as their sensors are temperature stabilized and therefore do not need black balancing.

Defect Pixels

All sensors exhibit some defect pixels. ARRI digital cameras deal with them via three methods. First, a static pixel correction map is created during manufacturing and during each re-calibration of the sensor. Second, the camera continuously monitors each pixel and masks defect pixels with the Dynamic Defect Pixel Correction (DDPC). And third, in the rare case where there are still unruly pixels, customers can create their own User Pixel Mask (UPM), as described in the ALEXA Mini LF manual under “20.3 User Pixel Masking”.

Recording Media

ALEXA Mini LF cameras record to Codex Compact Drive 1 TB magazines.