

A PTP Grandmaster with GPS, merged with a Precision Reference Generator



The DXD series from Brainstorm is designed to ease the transition to IP. The flagship model DXD-16 combines a PTP Grandmaster clock with a multi-format legacy reference generator. While working in a PTP environment, the DXD-16 keeps legacy equipment perfectly synchronized with the IP infrastructure, or vice-versa.

FEATURES

- **Flexibility and easy integration**
 - Synchronizes to a PTP network, a GPS clock or a legacy reference
 - PTP Grandmaster w/ 4 Ethernet ports
 - Supports PTP v1 (Dante), PTP v2 (AES67) and gPTP (AVB/Milan)
 - 16 User-Definable Outputs: WC, AES, Video Sync, 10MHz
- **Reliability**
 - Dual power sources w/ auto switch-over for redundancy
 - Dual references with shock-free transitions in case of failure
 - Battery power for internal TOD back-up clock
- **Security**
 - Independent Ethernet ports - no information flow between network ports
- **Upgradable (options)**
 - OCXO Oscillator
 - GPS Receiver
 - Dual Time Code generator (LTC)

NETWORK SYNC (1588 PTP)

The DXD-16 complies with IEEE 1588 PTP V2 and can be either a PTP Grandmaster, slave or Boundary Clock. PTP (Precision Time Protocol), defined in IEEE 1588, has been broadly adopted by manufacturers as a network synchronizing standard, which means that the DXD-16 can work in a number of systems. PTP profiles supported by the DXD-16 include AES67 and SMPTE 2059.

As a Boundary Clock, the DXD-16 can be a slave to a Grandmaster on one of its attached networks, synchronize its internal clocks to that Grandmaster, and distribute the same Grandmaster time in its role as PTP master to the remaining attached networks. Alternatively it can itself fulfill the function of Grandmaster and be PTP master on all attached networks.

The DXD-16 has four Gigabit Ethernet ports (RJ45). The different ports can be used independently or as primary and secondary pairs. Each network connector supports an electrically and logically independent network, with the DXD-16 acting as a PTP timing bridge. The DXD-16 is not a network switch, and for security reasons no information flows from any network port to any other.

REFERENCE GENERATOR WITH UNIVERSAL OUTPUTS

The DXD-16 generates up to 6 independent sync pulses and clocks simultaneously and routes them to the 16 BNC outputs. These outputs offer great flexibility compared to dedicated outputs as they can be configured by the user for any of the generated legacy reference signals. This includes all standard SD and HD video sync formats (Black Burst and HD tri-level sync), word clock and AES-3id (at rates from 32 to 384 KHz, plus all the necessary pull-up/down, including 24:25 conversions, even VSO) and 10MHz.

A high-accuracy internal crystal oscillator (TCXO) provides a very stable frequency reference (+/- 1ppm). External legacy signals can also be used as reference, such as Word Clock, AES, Video Sync (SD & HD) or a 10MHz tone. The generated outputs have extremely low jitter. The output rates are independent from the reference rate which means that any rate can be extracted from any reference such as 59.97 from 25FPS for example.

GNSS / GPS

An optional GNSS/GPS receiver can be installed in the DXD-16. It provides the highly accurate and stable GPS clock and Time Of Day (TOD) as an external timing source. With this function multiple DXD-16's in remote locations will be locked to each other and in phase once they are GPS referenced.

RESILIENCE & REDUNDANCY

When using an external reference, a second identical source can be connected as fallback in case of failure. If the external reference becomes unusable, the DXD-16 continues generating, locked either to the alternate source or to the internal oscillator and re-locks to the reference when it reappears. These transitions occur smoothly and gradually with no sync shock to the system.

The internal time-of-day clock is powered by a battery to keep it running while power is off.

An internal 100-240 VAC power supply is provided as is a DC input for an external 12VDC source. The unit can operate with either of these power sources and either can act as a back-up for the other with auto switch-over in the event of a failure.

ALARM & REMOTE CONTROL

GPI inputs (3) and outputs (3) are included.

All functions and settings can be monitored and altered via a web browser.



For sales and product information:

Main Office

info@plus24.net

8974 Kramerwood Place - Los Angeles, CA 90034 - USA

Tel: +1 (323) 845-1171 • Fax: +1 (323) 845-1170

plus24
www.plus24.net

European Office:
 BEE DISTRIBUTION

info@beedistribution.com

60 rue Jules Lejeune - 1050 Brussels - BELGIUM

Tel: +32 498/ 52 54 11

OPTIONS

- **OCXO** (hardware): An oven-controlled-oscillator (OCXO) is available as an option, providing greater long-term time and TOD accuracy (± 10 ppb, which is less than ± 10 frames per year). The greater accuracy is also useful in GPS systems where extended GPS dropouts may be expected.
- **GNSS/GPS Receiver** (hardware): A GNSS/GPS receiver can be installed in the DXD-16. This option includes an SMA antenna input connector. (Antenna not included.)
- **Time Code** (firmware): The LTC option enables the DXD-16 to generate 2 separate streams of time code simultaneously. They can be routed to the BNC outputs and to the 2 balanced time code outputs on the DB25 connector. Two modes exist: Time-of-Day or simple Run/Stop/Cue.

DXD-16 Universal Clock Specifications

PTP

Complies with PTP v1, v2 and gPTP
Unicast / Multicast operation
Configurable as a Grandmaster, slave or Boundary clock
4 Independent Gigabit Ethernet ports (RJ-45)

SYNCHRONIZATION SOURCES

GPS
PTP
Word clock
AES
Video sync (Black Burst or HD tri-level sync)
10MHz

GPS SOURCES (option)

- SMA antenna input for external GPS antenna (not included)

USER ASSIGNABLE INPUTS

2 BNC input connectors (75 Ω) accept the following:

- Word clock
- AES
- Video sync (Black Burst or HD tri-level sync)
- 10 MHz

LEGACY GENERATOR

Generates simultaneously up to 6 different rates in any of these formats:

- Word clock - rates from 32 to 384 KHz
- AES - rates from 32 to 96 KHz
- Video sync:
 - NTSC/PAL black burst
525/29.97/30i
625/23.98/24/25i
 - HD tri-level sync
720/23.98/24/25/29.97/30/50/59.94/60P
1080/25/29.97/30i
1080/23.98/24/25/29.97/30sF
1080/23.98/24/25/29.97/30/50/59.94/60p
- 10 MHz
- Time Code (option)

USER ASSIGNABLE OUTPUTS

16 outputs - in 6 groups
BNC - 75 Ω
Output signal: any of the generated legacy references

TIME CODE OUTPUTS (option)

Time Code streams can be sent via the following:

- Unbalanced: any of the BNC output groups
- Balanced: 2 outputs provided on the DB25 connector

OSCILLATOR

TCXO: ± 1 ppm
OCXO (option): ± 10 ppb

BATTERY BACKUP

The internal back up clock, the RTC (Real Time Clock) is powered by a battery to keep it running while power is off

REMOTE CONTROL

3 GPI inputs (DB-25)
Web browser (requires firmware 3.00 or later)

ALARM

3 GPI outputs (DB-25)

PRESETS

10 presets can be programmed for quick recall

DISPLAY

2.4" TFT LCD - 240 x 320 resolution

POWER

100-240 VAC
12 VDC @ 5A
With auto switch-over for redundancy

WEIGHT & nDIMENSIONS

3.97 lbs (net) - 19" x 1.75" x 8"

www.brainstormtime.com

plus24
www.plus24.net

For sales and product information:

Main Office

info@plus24.net
8974 Kramerwood Place - Los Angeles, CA 90034 - USA
Tel: +1 (323) 845-1171 • Fax: +1 (323) 845-1170

European Office:

BEE DISTRIBUTION

info@beedistribution.com
60 rue Jules Lejeune - 1050 Brussels - BELGIUM
Tel: +32 498/ 52 54 11