



Surge Protector and Power Conditioner



1080 JOULES OF SURGE PROTECTION



POWER CONDITIONING & NOISE REDUCTION




FLEXIBLE ARMS MAKE IT EASY TO USE POWER PLUGS & TRANSFORMERS

POWERSQUID SURGE PROTECTOR

The PowerSquid® Surge Protector and Power Conditioner is a safe and easy way to provide 1080 joules of surge protection to your sensitive electronics. The PowerSquid accommodates up to 5 bulky transformer plugs with ease, providing more flexibility than a standard surge protector.

The PowerSquid Noise Reduction Filter reduces line static caused by "dirty" power. Line noise and electrical static can show up as snow in your picture or as crackling in your audio. The filter isolates your equipment from power generated noise for a clear picture and sound.





Specifications:

Electrical Rating: 120V, 15Amps, 1800 Watts

Maximum Energy Dissipation: 1080 JOULES

Maximum Spike Current: 72,000 AMPS UL-1449 3rd. Edition

Clamp Rating: H-N 400V H-G 400V N-G 400V

Response Time: Instantaneous (Less than 1 Nanosecond)

Circuit Breaker: 15 AMPS (Resettable)

Protection Working Indicator: Red LED

Ground Power Indicator: Green LED

Power Indicator: Green LED

EMI/RFI Noise Reduction: Up to 40dB from 150KHz to 100MHz

3 ft. Heavy Duty Grounded Power Cord

2-Way Wall Mountable Rubber Feet Prevent Sliding

Drop Tested ABS Housing

Recessed Master Power Button Prevents Accidental Switching

> Accell Corporation Tel 877.353.0772 Fax 510.252.1178 sales@accellcables.com

www.accellcables.com







Product

PowerSquid - 1080J

Part Number

UPC Code

D080B-008K

826388106574